

Product Code: CSP042

Description: 2 x 100W 2 Gang Smart Switching Receiver



General Information

| | | |
|--|---|--|
| Dimensions (mm) | 46 (W) x 46 (H) x 18 (D) | |
| Finish | White | |
| Materials | Housing: Polycarbonate | Electronics: PCB & Electronic Components |
| Rated Voltage (V~) (Ue) | 220-240 | Frequency (Hz) 50/60 |
| Load Rating (W) | 100 (x2) | |
| Load Rating Comments | LED | |
| Termination Type | Screw | |
| Terminal Size (mm) | 3 x 2 | Terminal Torque Value (Nm) 0.2 |
| Terminal Capacity - Solid (mm²) | 3 x 1.5 | Signal Transmission Frequency 2.400 to 2.484GHz |
| Protocol | Zigbee | |
| Open Air Wireless Range (M) | < 100 | |
| Standby Current (mA) | 1 | |
| Working Current (mA) | 10 | |
| Indicator Colour | Blue | |
| Minimum Back Box Depth (mm) | 35 (47 Flat Plate) | |
| Ingress Protection | IP20 | |
| Working Humidity | 10%-90%RH | |
| Operational Temperature (°C) | -10 to +40 | |
| Warranty (Years) | 2 | |
| Standards | BS EN 60669-2-1 BS EN 55035 BS EN 61000-3-2 BS EN 61000-3-3 BS EN 62311 | |

Additional Information No neutral connection required
Zigbee signal mesh
Utilises standard 230V switch wiring with permanent live required
Voice control via ClickSmart+ Hub using Alexa and/or Google Home

Components Supplied Switching Receiver, Mounting Bracket (DIN Rail Mountable or Screw Fixable), Instruction Manual

Installation Overview No neutral connection required.
Utilises standard on/off switches
Utilises standard switches and switch wiring
Can be multi-way switch controlled along with control via the ClickSmart+ app

Programming Information With hub and app setup and receiver wired and powered, if not in pairing mode press the switch 'On' and 'Off' five times, the receiver LED will start flashing or the switch 'On' and 'Off' no longer operates to confirm in pairing mode. Can be paired with hub via app.