



Pendant

WARNINGS

- This is a Class I product and must be earthed.
- Please read these instructions carefully before commencing any work and keep them for future reference. It is recommended that this fitting is installed by a qualified electrician.
- Install in accordance with the current IEE Wiring regulations and current Building Regulations.
- To prevent electrocution switch off at mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electrical supply without your knowledge. If you are in any doubt, please consult a qualified electrician.
- This light fitting should be connected to the lighting circuit in your home.
- If replacing an existing fitting, make a note of the connections.
- Always use the correct type and wattage bulb. Never exceed the wattage stated.
- When changing a bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.
- This product is suitable for indoor use only, on normally flammable surfaces.

SPECIFICATION

Power Source: 240V~50Hz
 Class: Class I (Earthed)
 Recommended Bulb: 42W E27 Eco GLS
 LED: 9-11W LED Classic Clear Bulb
 Suitable for use with a dimmer: Yes (Some energy saving bulbs are not suitable for use with a dimmer switch).
 Outdoor use: No
 Weight: 1.3kg

INSTALLATION INSTRUCTIONS

Make sure you have the following items which are required to install this light fitting:

- Small electrical screwdriver, cross head screwdriver & insulation tape.
- The installation of this fitting will be much easier with the help of an assistant.

Before removing the existing fitting, **carefully note the position of each set of wires.** Where a ring/loop circuit exists there will be a fourth set of wires (usually red) that are not connected to the L, N, or E. of the fitting. This circuit must be kept together in the spare terminal of the connection block, and insulated from the fitting and the other wires. **The ring/loop will remain live unless isolated at the mains or circuit breaker regardless of the position of the wall switch.**

Height adjustment

This will be easier to complete before attaching the product to the ceiling and can be achieved in two ways. Firstly, work out the new height at which the product will hang. Then to reduce the length of cable drop, unscrew the clamp screw inside the ceiling cover and retighten the cable clamp once desired drop is reached. Secondly, chain links can be removed to reduce the drop of the product. Unscrew the carabiner (A) on the bottom chain link and remove unwanted links before retightening it. Always ensure that the weight of the fitting is supported by the chain and not the cable. **Refer to Assembly Diagrams 2 & 3.**

Remove the fixing bracket from the ceiling cover by removing side screws and attach to the ceiling using the screws provided. Ensure there is a joist at the point of fixing to support the weight of the product. Take care to avoid damaging any concealed wiring and pipes. **Refer to Assembly Diagram 4.**

Having identified the household wiring from your existing light fitting, connect to the connection block inside the product as shown in **Assembly Diagram 5.** A spare terminal block is supplied should a loop connection be required.

Check that.... You have correctly identified the house wires, the connections are tight, no loose strands have been left out of the connection block., and all exposed areas of the connection block are covered with 2 layers of insulation tape.

This product has "L" shaped fixing slots to allow easy fixing to the ceiling strap. Locate the "L" slots around the small screws on the ceiling strap. Rotate the ceiling cover to attach the product to the strap. Tighten the screws to secure. Take care not to trap any wiring. **Refer to Assembly Diagram 6.**

Fitting/Replacing the bulb - Max. 42W E27 Eco GLS

When changing a bulb, always switch off at the mains and allow the bulb to cool before handling. Dispose of used bulbs carefully. Do not exceed the wattage stated or use a different shape bulb from that indicated on the fitting. **Refer to Assembly Diagram 7.**

Fitting the glass shade

To fit the glass shade, align the three holes in the glass shade with the securing screws in the metal shade. Carefully tighten the screws ensuring holes are accurately aligned to avoid breakage. **Refer to Assembly Diagram 7.**

Replace fuse or circuit breaker and switch on. Your light is now ready for use. **Refer to Assembly Diagram 7.**

Care and cleaning

We recommend cleaning with a soft dry cloth. Do not use abrasive materials as these will damage the finish.

Safety Information

For your safety, always switch off the supply before changing lightbulbs, cleaning or removing shades.

Waste electrical products should not be disposed of with household waste. Separate disposal facilities exist, for nearest facilities see www.recycle-more.co.uk or in-store for details.

