DATASHEET

making connections beautifully


Hamilton

Code: 76FOCSC-B Hartland | HARTLAND RANGE | Connection Units


Product Image



Wiring



Dimensions



Insert Type	1 gang 13A Fuse + Cable Outlet
Insert Colour	Satin Chrome/Black
EAN13 Barcode	5017503266968
Commodity Code	85361050
Luckins TSI	385554679
Dimensions(Nominal)	Single: Height = 88.0mm Width = 88.0mm Depth = 5.0mm
Switched Poles	None
Current Rating	13 Amp
Voltage	220/250V AC
Maximum Load	13 Amp
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	None
Terminal Capacity 1	5 x1mm²
Terminal Capacity 2	4x1.5mm²
Terminal Capacity 3	3x2.5mm²
Terminal Capacity 4	1x4mm² Multi-strand
Terminal Capacity 5	1x6mm²
Earth Terminal Capacity 1	6x1mm²
Earth Terminal Capacity 2	5x1.5mm²
Earth Terminal Capacity 3	3 x2.5mm²
Earth Terminal Capacity 4	2x4mm² Multi-strand
Earth Terminal Capacity 5	1x6mm²
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS 1363-4

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

 $\textbf{E:} info@hamilton-litestat.com | \textbf{W:} www.hamilton-litestat.com | \textbf{W$

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. This datasheet was generated on 3/6/2023 4:48:28 PM E&OE