DATASHEET




Code: 79CT21

Hartland CFX | HARTLAND CFX RANGE | Toggle Switches


Product Image



Wiring



Dimensions



Insert Type	1 gang 20AX 2 Way Toggle
Insert Colour	
EAN13 Barcode	Antique Brass
	5017504299255
Commodity Code	85363030
Luckins TSI	388242014
Dimensions(Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm
Weight	200 GR
Switched Poles	Single
Current Rating	20AX
Voltage	220/250V AC
Maximum Load	20 Amp inductive
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	5x1mm²
Terminal Capacity 2	4x1.5mm²
Terminal Capacity 3	2x2.5mm²
Terminal Capacity 4	2x4mm² Multi-strand
Terminal Capacity 5	1x6mm²
Earth Terminal Capacity 1	6x1mm²
Earth Terminal Capacity 2	5x1.5mm²
Earth Terminal Capacity 3	3x2.5mm²
Earth Terminal Capacity 4	2x4mm² Multi-strand
Earth Terminal Capacity 5	1x6mm²
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS EN 60669-1

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | **W:** www.hamilton-litestat.com

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.